

Connect Core™ Server (for Small Deployments)

Note: The same version of CenTrak's Core Software will be used regardless of deployment size. However, servers with reduced requirements may be used. See below for minimum requirements suitable for smaller deployments



Supported Operating Systems

Windows Server 2008 R2, 2012 R2, 2016, 2019

Minimum Hardware Requirements

Server can be a Virtual Machine or Physical Server

Processor	Dedicated Dual Core Processor running at 2.75 GHz or higher Virtualized systems should have at least the 2 cores dedicated, and not shared, across other software applications.
Memory	4 to 8 GB RAM
Hard Drive	250 GB local disk space for application components, backups, and log-files Minimum 15k RPM
Network Adapter	Dedicated 1Gbps connection

Network

Remote Connectivity	Remote access process for CenTrak personnel to access the CenTrak server for installation, administration, maintenance and troubleshooting. Local access to server from within facility network. <ul style="list-style-type: none"> - E.g. RDP access from CenTrak laptop while onsite - Web browser access to server with supported web based applications
Communication Speed	Maximum of 7 milliseconds round trip communication for all wired nodes (server, star, timing controller and security controller).

CenTrak products do not support the Connect Core Software to be used over public internet connections due to uncontrollable latency issues. CenTrak's Location and Sensing Services should always meet the timing constraints of the system specifications over averaged time, not single point tests, which is typically not possible outside of private networks.

Required Applications

- Microsoft Internet Explorer 9 (or above) or Google Chrome
- JavaScript support must be enabled
- Adobe Reader
- WinRAR 3.0 or above (license to be acquired by customer)
- Microsoft .NET Framework 4.0 or above

Internet Protocol Addressing

	Static	DHCP or Static
IP Addresses	Server Timing Controller	Stars Security Controllers

Supported Devices

Device Type	Tags - Qty. 100 Stars - Qty. 10	Any combination of Monitors, Virtual Walls, LF Exciters, and Hand Hygiene Sensors Deployment with Stars: Qty. 50 Deployment without Stars: Qty. 100

For systems which plan to exceed any of the above device quantities, please contract CenTrak. Please supply which device type will be exceeded, the total quantity of the device type and current server system hardware specifications for review.

Port Configuration

The following Ports need to be opened for the CenTrak RTLS Server.

Device	Ports	Protocol
Star	7070, 4747, 6128, 3030, 5051, 5050, 5580	UDP, TCP
Wi-Fi Associating Devices	5757	UDP
Cisco MSE or CMX	9292, 4567, 443	UDP, TCP
Cisco DNA Spaces	10309	TCP
Aruba ALE	7117, 7779, 443	UDP, TCP
External Applications	7170 to 7270	UDP
Security Solutions Server	8181	TCP
Security Solutions SQL Server	1433	TCP

Network Security Configuration

Criteria	Reason
Need to configure anti-virus software to exclude scanning and live protection on all CenTrak folders (e.g. C:\CenTrak, "C:\Program Files\CenTrak")	CenTrak software continuously writes data to storage. Due to the format of the file and consistency of the writing, anti-virus and other security software will monitor and block these writes. The entire folder will need to be excluded from both periodic scanning and being monitored in real time.
Need to exclude network monitoring / firewall software from all CenTrak folders	CenTrak software makes many network connections with the various CenTrak hardware deployed. Network monitoring software will intercept network communications and scan for signatures. This process slows down the ability of CenTrak to provide locations and alerts in real time, and in some cases, CenTrak software is completely shut down due to the intrusive security measures.
Need to open all ports in Firewall for the local network access	CenTrak software will communicate using UDP and TCP through several different ports to CenTrak hardware. Therefore, the CenTrak server should be able to communicate to any CenTrak hardware inside the network. If there are any restrictions on internal (within the network) communication, exceptions need to be provided to CenTrak server to be able to communicate to all CenTrak hardware.
<p>Connect Pulse™ access: outbound access to the following URLs need to be open from the CenTrak server. All TCP connections require inbound traffic (not connection). No other inbound access needed. Firewall settings should reference hostnames and not IP addresses as IP addresses are subject to change. Exclude the proxy settings for the Pulse sites and ports. In HTTP/HTTPS calls, the firewall / proxy server should not modify the request headers and should support authentication headers.</p> <ul style="list-style-type: none"> ✓ gms.centrak.com - Ports 443 (TCP) ✓ gmsdata.centrak.com - Ports 443 (TCP) ✓ gmsrtdata.centrak.com - Port 10309 (TCP) ✓ api.centrak.com - Port 443 (TCP) 	<p>Transfer log files for maintenance and access in CenTrak Connect Pulse Portal.</p> <p>Proxy servers tend to block files from being transferred. Pulse needs the RTLS equipment log files to be uploaded from the on-site server to the Pulse cloud server.</p> <p>Note: Starting with Connect Core versions 5.14 SP23 GA (Pegasus) and 5.15 SP8 GA (Orion), TCP Port 80 for all URLs is not required or used and api.centrak.com (TCP Port 443) is required.</p>